

Application No. 10/696,989

MICI 1001-2

In the claims:

This listing of claims will replace all prior versions and listings of claims in the application:

- 1 1. (currently amended) A method of operating a laser to obtain an output pulse of laser radiation
2 having a single wavelength, the laser including a resonator with an output coupler, a gain
3 medium positioned inside the resonator and a pump source, the method comprising:
4 inducing an intracavity loss into the resonator by setting a reflectivity of the output
5 coupler, the loss being an amount that prevents oscillation during a time that energy from the
6 pump source is being stored in the gain medium;
7 building up gain with energy from the pump source in the gain medium until formation of
8 a single-frequency relaxation oscillation pulse in the resonator; and
9 reducing the intracavity loss induced in the resonator upon the detection of the relaxation
10 oscillation pulse by increasing the reflectivity of the output coupler, so that built-up gain stored
11 in the gain medium is output from the resonator as [[a]] an output pulse at the single frequency.
- 1 2. (original) The method of claim 1, wherein
2 the gain medium comprises a neodymium-doped solid-state material, and the single
3 frequency is approximately 1.05 microns.
- 1 3. (original) The method of claim 1, wherein said pump source comprises a source of optical
2 energy.
- 1 4. (original) The method of claim 1, wherein said pump source comprises a flashlamp.
- 1 5. (original) The method of claim 1, wherein said pump source comprises one or more laser
2 diodes.
- 1 6. (original) The method of claim 1, wherein the resonator includes a Q-switch and polarizer,
2 and said reducing comprises controlling the Q-switch.

Application No. 10/696,989

MICI 1001-2

1 7. (original) The method of claim 1, wherein the resonator includes an electronically controlled
2 Pockels cell, and said reducing comprises controlling the Pockels cell.

1 8. (original) The method of claim 1, including generating a plurality of output pulses having
2 substantially constant pulse amplitude and pulse width by repeating said inducing, building up
3 and reducing steps.

1 9. (original) The method of claim 1, wherein the output pulse has a pulse width of less than 30
2 nanoseconds, full-width half-maximum.

1 10. (original) The method of claim 1, wherein the resonator includes an output coupler having a
2 controllable reflectivity, and including controlling the reflectivity of output coupler to establish a
3 desired pulse width.

1 11. (original) The method of claim 1, wherein the resonator includes an output coupler
2 comprising a polarizing beam splitter, and including controlling the reflectivity of output coupler
3 by controlling polarization inside the resonator.

1 12. (original) The method of claim 1, wherein the resonator includes an output coupler
2 comprising a polarizing beam splitter, and said inducing intracavity loss includes setting an
3 amount of intracavity light that is transmitted by the polarizing beam splitter.

1 13. (original) The method of claim 1, wherein the resonator includes an output coupler
2 comprising a polarizing beam splitter, and said inducing intracavity loss includes inserting a
3 polarization rotation element in the resonator to set an amount of light that is transmitted by the
4 polarizing beam splitter.

1 14. (original) The method of claim 1, wherein the resonator includes an electronically
2 controlled Pockels cell, and the resonator includes an output coupler comprising a polarizing
3 beam splitter, and including controlling the reflectivity of output coupler by controlling
4 polarization inside the resonator using the Pockels cell.

Application No. 10/696,989

MICI 1001-2

1 15. (original) The method of claim 1, wherein the resonator includes an electronically
2 controlled Pockels cell, and said reducing comprises controlling voltage pulses applied to the
3 Pockels cell, and wherein the resonator includes an output coupler comprising a polarizing beam
4 splitter, and including controlling the reflectivity of output coupler by controlling the voltage
5 pulses applied to the Pockels cell during said reducing.

1 16. (original) The method of claim 1, including detecting an onset of the relaxation oscillation
2 pulse prior to a peak of the relaxation oscillation pulse, at a point occurring at less than 5% of
3 average peak power of such pulses.

1 17. (original) The method of claim 1, including detecting an onset of the relaxation oscillation
2 pulse prior to a peak of the relaxation oscillation pulse, at a point occurring at less than 1% of
3 average peak power of such pulses.

1 18. (original) The method of claim 1, wherein the resonator includes a Q-switch and a polarizer,
2 and including detecting an onset of the relaxation oscillation, and the reducing includes applying
3 a control signal to the Q-switch in response to the detected onset prior to a peak of the relaxation
4 oscillation pulse.

1 19. (original) The method of claim 1, including positioning an aperture within the resonator to
2 allow a single transverse mode in the output pulse.

1 20. (original) The method of claim 1, wherein the resonator comprises a ring having an odd
2 number of reflectors.

1 21. (original) The method of claim 1, wherein the resonator comprises a ring, an including
2 suppressing oscillation in one direction within the ring with components acting as an optical
3 diode.

1 22. (currently amended) A laser system, comprising:
2 a laser resonator, comprising an output coupler with an adjustable reflectivity;
3 a Q-switch in the resonator;

Application No. 10/696,989

MICI 1001-2

4 a gain medium in the resonator;
5 a source of energy, coupled with the gain medium, to pump the gain medium;
6 a detector, coupled with the resonator, to detect oscillation energy in the resonator; and
7 a controller, coupled to the source of energy, the Q-switch and the detector, to set the
8 adjustable reflectivity of the output coupler to establish conditions inducing loss in the resonator
9 at a level allowing build up of gain in the gain medium to produce a relaxation oscillation pulse,
10 and to decrease loss in the resonator by increasing the adjustable reflectivity of the output
11 coupler, using the Q-switch in response to detection of the relaxation oscillation pulse, so that an
12 output pulse having a single frequency is generated.

1 23. (canceled)

1 24. (original) The system of claim 22, wherein said output coupler comprises a polarizing beam
2 splitter.

1 25. (original) The system of claim 22, including an etalon in the resonator arranged so that
2 reflections of undesirable wavelengths are not coupled back into the resonator.

1 26. (original) The system of claim 22, including a set of etalons in the resonator adapted to
2 restrict oscillation to a single longitudinal cavity mode.

1 27. (original) The system of claim 22, wherein the Q-switch comprises a Pockels cell, and the
2 output coupler comprises a polarizing beam splitter.

1 28. (original) The system of claim 22, wherein the gain medium comprises a neodymium-doped
2 solid-state material, and the single frequency is approximately 1.05 μm .

1 29. (original) The system of claim 22, wherein said pump source comprises a source of optical
2 energy.

1 30. (original) The system of claim 22, wherein said pump source comprises a flashlamp.

Application No. 10/696,989

MICI 1001-2

1 31. (original) The system of claim 22, wherein said pump source comprises a laser diode.

1 32. (original) The system of claim 22, wherein the detector detects an onset of the relaxation
2 oscillation prior to a peak of the relaxation oscillation pulse.

1 33. (original) The system of claim 22, wherein the detector detects an onset of the relaxation
2 oscillation, and the controller applies a control signal to the Q-switch in response to the detected
3 onset.

1 34. (currently amended) A laser system, comprising:
2 a laser resonator, comprising an output coupler;
3 a Q-switch in the resonator;
4 a gain medium in the resonator;
5 a source of energy, coupled with the gain medium, to pump the gain medium;
6 a detector, coupled with the resonator, to detect oscillation energy in the resonator; and
7 a controller, coupled to the source of energy, the Q-switch and the detector, to set
8 conditions inducing loss in the resonator at a level allowing build up of gain in the gain medium
9 to produce a relaxation oscillation pulse, and to decrease loss resonator in response to detection
10 of the relaxation oscillation pulse, so that an output pulse having a single frequency is generated
11 ~~The system of claim 22,~~ wherein the resonator is arranged as an optical ring, and including
12 optical components in the resonator acting as an optical diode.

1 35. (original) The system of claim 22, wherein the resonator is arranged as an optical ring
2 having an odd number of reflectors.

1 36. (original) The system of claim 22, wherein the resonator is arranged as an optical ring
2 having an odd number of reflectors, including a flat reflector having an adjustable mount setting
3 an angle of reflection, whereby adjustments of a length of the optical ring can be made by
4 adjusting the angle of reflection of the flat reflector.

1 37. (original) The system of claim 22, including a transverse mode limiting aperture in the laser
2 resonator.

Application No. 10/696,989

MICI 1001-2

1 38. (original) The system of claim 22, wherein the output coupler comprises a polarizing beam
2 splitter, and including a polarization rotation element in the resonator to set an amount of light
3 that is transmitted by the polarizing beam splitter during build up of gain.

1 39. (currently amended) The system of claim 22, wherein ~~said output coupler comprises an~~
2 ~~output coupler having an adjustable reflectivity, and the controller sets [[an]] the adjustable~~
3 reflectivity of the output coupler to establish a pulse width.

1 40. (currently amended) The system of claim 22, wherein the Q-switch comprises a Pockels
2 cell, and the output coupler comprises a polarizing beam splitter, and the controller applies an
3 adjustable voltage to the Pockels cell when reducing loss in the resonator, the adjustable voltage
4 establishing the adjustable ~~an amount of~~ reflectivity of the output coupler to establish a pulse
5 width.

1 41. (currently amended) The system of claim 34 22, wherein the output coupler comprises a
2 polarizing beam splitter, and including a polarization rotation element in the resonator to set an
3 amount of light that is transmitted by the polarizing beam splitter during build up of gain.

1 42. (original) A laser system, comprising:
2 a laser resonator arranged as an optical ring, comprising a polarizer and a polarizing
3 beam splitter arranged as an output coupler;
4 an optical diode in the resonator;
5 one or more etalons in the resonator;
6 a Pockels cell in the resonator;
7 a gain medium in the resonator;
8 a source of energy, coupled with the gain medium, to pump the gain medium;
9 a detector, coupled with the resonator, to detect oscillation energy in the resonator; and
10 a controller, coupled to the source of energy, the Pockels cell and the detector, to set
11 conditions inducing loss in the resonator at a level allowing build up of gain in the gain medium
12 to produce a relaxation oscillation pulse, and conditions decreasing loss resonator using the
13 Pockels cell in response to detection of onset of the relaxation oscillation pulse, so that an output
14 pulse having a single frequency is generated, and applying an adjustable voltage to the Pockels

Application No. 10/696,989

MICI 1001-2

15 cell to adjust polarization within the resonator and thereby reflectivity of the polarizing beam
16 splitter arranged as the output coupler, to set a pulse width during said conditions decreasing
17 loss.

1 43. (original) A method of operating a laser to obtain an output pulse of laser radiation having a
2 single wavelength, the laser including a resonator arranged as an optical ring, a gain medium
3 positioned inside the resonator and a pump source, the method comprising:
4 suppressing oscillation in one direction within the ring with components acting as an
5 optical diode;
6 suppressing oscillation within the ring at wavelengths other than the single wavelength;
7 using a polarizing beam splitter as an output coupler;
8 setting polarization inside the resonator to induce an intracavity loss into the resonator,
9 the loss being an amount that prevents oscillation during a time that energy from the pump
10 source is being stored in the gain medium;
11 building up gain with energy from the pump source in the gain medium until formation of
12 a single-frequency relaxation oscillation pulse in the resonator; and
13 changing polarization inside the resonator to reduce the intracavity loss induced in the
14 resonator and to set a reflectivity of the polarizing beam splitter upon the detection of the
15 relaxation oscillation pulse so that built-up gain stored in the gain medium is output from the
16 resonator as a output pulse at the single frequency having a pulse width determined by the
17 changed polarization.

1 44-56. (canceled).

1 57.(new) A method of operating a laser to obtain an output pulse of laser radiation having a
2 single wavelength, the laser including a resonator configured as a ring, a gain medium positioned
3 inside the resonator and a pump source, the method comprising:
4 inducing an intracavity loss into the resonator, the loss being an amount that prevents
5 oscillation during a time that energy from the pump source is being stored in the gain medium;
6 building up gain with energy from the pump source in the gain medium until formation of
7 a single-frequency relaxation oscillation pulse in the resonator; and

Application No. 10/696,989

MICI 1001-2

8 reducing the intracavity loss induced in the resonator upon the detection of the relaxation
9 oscillation pulse so that built-up gain stored in the gain medium is output from the resonator as a
10 output pulse at the single frequency; and
11 suppressing oscillation in one direction in the ring using components acting as an optical
12 diode.

1 58. (new) The method of claim 57, including restricting oscillation in the resonator to a
2 single longitudinal mode using one or more etalons placed at or near normal incidence.

1 59. (new) The method of claim 57, including restricting oscillation in the resonator to a
2 single longitudinal mode using one or more etalons, and suppressing reflections from the one or
3 more etalons.

1 60. (new) The method of claim 57, including
2 restricting oscillation in the resonator to a single longitudinal mode using one or more
3 etalons placed at or near normal incidence;
4 temperature stabilizing the one or more etalons in the resonator; and
5 suppressing reflections from the one or more etalons.

1 61.(new) The method of claim 57, wherein the ring has an odd number of reflectors.

1 62.(new) The system of claim 34, including one or more etalons in the resonator placed at or
2 near normal incidence.

1 63.(new) The system of claim 34, including one or more etalons in the resonator, and including
2 optical components in the resonator acting as an optical diode suppressing reflections from the
3 one or more etalons.

1 64.(new) The system of claim 34, including one or more temperature stabilized etalons in the
2 resonator placed at or near normal incidence, and including optical components in the resonator
3 acting as an optical diode suppressing reflections from the one or more etalon.